

PSB-60-G CABINET				MAX. POWER CALCULATION				110	110	110	
			SUM PCS				WATTS				
Modul	V	A	W	PCS	A3	A2	A1	A3	A2	A1	WALL
USB CHARGER	5	2,00	10	40	8	16	16	80,00	160,00	160,00	
RADIO CHARGER	110	0,14	15	20	4	8	8	60,00	120,00	120,00	
RFID READER	3,3	0,33	1,1	20	4	8	8	4,40	8,80	8,80	
KEY LOCKER+LIGHT	12	0,20	2,4	20	4	8	8	9,60	19,20	19,20	
KONTROLLER	3,3	0,33	1,1	20	4	8	8	4,40	8,80	8,80	
Smart Station	12	2,50	30	1	1	0	0	30,00	0,00	0,00	
SUM WATTS								188,40	316,80	316,80	822,00
SUM AMPS								1,71	2,88	2,88	7,47
BREAKER AMPS								6	6	6	20

PSB-60-G CABINET				MIN. POWER CALCULATION				110	110	110	
			SUM PCS				WATTS				
Modul	V	A	W	PCS	A3	A2	A1	A3	A2	A1	WALL
USB CHARGER	5	2,00	10	40	0	0	0	0,00	0,00	0,00	
RADIO CHARGER	110	0,14	15	20	0	0	0	0,00	0,00	0,00	
RFID READER	3,3	0,33	1,1	20	4	8	8	4,40	8,80	8,80	
KEY LOCKER+LIGHT	12	0,20	2,4	20	4	8	8	9,60	19,20	19,20	
KONTROLLER	3,3	0,33	1,1	20	4	8	8	4,40	8,80	8,80	
Smart Station	12	2,50	30	1	1	0	0	30,00	0,00	0,00	
SUM WATTS								48,40	36,80	36,80	122,00
SUM AMPS								0,44	0,33	0,33	1,11
BREAKER AMPS								6	6	6	20